



An ISO 9001:2015 Co.

BJT (Transistorized) Series Voltage Regulator (SVR) with Digital Meters

Model : SB-108DM

SINCOM SB-108DM BJT (Transistorized) Series Voltage Regulator with Digital meters is remarkable self contained simply designed trainer to study the operation, line and load regulation characteristics of BJT Series Voltage Regulator with variable load in a simple experimental way. The Trainer is equipped with on board Digital voltmeter & Digital Ammeter.

Features

- ❖ User friendly Design
- ❖ Silicon NPN Transistorized circuit with one Zener Diode as controlling element
- ❖ Facility to vary wide range of applied DC Input voltage
- ❖ Variable Resistive Load
- ❖ Facility to vary regulated Output DC Voltage
- ❖ In-Built Variable regulated DC Power Supply
- ❖ Very Easy for Operation
- ❖ Multi color Circuit Diagram printed on the front panel of the white board.
- ❖ Enclosed in an attractive, light weight, High Quality, Poly Coated Imported Pine Wooden cabinet
- ❖ On Board 3^{1/2} Digit Digital Voltmeter and Ammeter
- ❖ Interconnections by 2mm high quality banana sockets and pins
- ❖ Maximum Test points to explore all the corners of experiment
- ❖ 1 Year Warranty

Technical Specifications

- | | |
|----------------------------|---------------------------------------------------|
| ▪ AC Mains Power Supply | : 230V ±10%, 50Hz |
| ▪ DC Power Supply | : IC Regulated Variable 0V to +12V/500mA |
| ▪ Unregulated DC Input Vin | : 0 to 12V DC Input |
| ▪ Regulated DC Output Vo | : Variable @ 6V to 11V |
| ▪ Output Voltage Control | : By 10KΩ Potentiometer at sampling network |
| ▪ Transistors Used | : Two No-BJT NPN Silicon- SL100 and BC548 |
| ▪ Forward Voltage Drop | : 1.2V at T _A = 25 ⁰ c |
| ▪ Load Resistor | : 10KΩ Variable Resistive Load |
| ▪ Regulation type | : Line and Load Regulation |
| ▪ Total Digital Meters | : 03 (2 Voltmeter and 1 Ammeter) |
| ▪ Digital Voltmeter | : 0-20V (2 No.) |
| ▪ Digital Ammeter | : 0-20mA (1No.) |
| ▪ Meter Display | : Red Color, 3 ^{1/2} Digit , LED Display |
| ▪ Weight | : 2.0 kg (approx) |
| ▪ Dimensions (mm) | : L 220 x W 270 x H 110 |
| ▪ Interconnections | : 2mm Banana sockets |
| ▪ Operating Temperature | : 0-50 ⁰ C, 80% RH |



An ISO 9001:2015 Co.

Learning Scope

- To Study operation of Series Voltage Regulator using Transistor.
- To Study Change in O/P Voltage w.r.t. change in I/P Voltage with Load RL constant (Line Regulation)
- To Study Change in O/P Voltage w.r.t change in Load RL with I/P voltage constant (Load Regulation)

Other Instruments Required

SINCOM Digital Multi VI meter (DMVI) : Model DMVI-03 Range V_1 -20V, I_1 -20mA, V_2 -20V, I_2 -200mA DC

Accessories Included : Set of Patch Cord and Details Instruction Manual